

# CISCO RFGW-1



## RF GATEWAY 1

The Cisco RF Gateway 1 is a standards-based universal edge QAM (U-EQAM) solution for convergence of high-speed and high-bandwidth data and video distribution at the edge of the cable access network. The Cisco RF Gateway 1 offers leading edge density, modularity, and flexibility with support for Switched Digital Video (SDV), VoD, Broadcast Video, and DOCSIS® 3.0/Modular CMTS (M-CMTS)™ all on a single QAM platform.

The Cisco RF Gateway 1 provides higher density (up to 96 QAMs per RU), improved reliability, superior RF performance, 1 GHz RF output, and DOCSIS 3.0/M-CMTS capability. It is fully integrated and tested as part of the Cisco Digital Broadband Delivery System (DBDS) and the Cisco uBR10012 M-CMTS solution, accelerating the deployment and easing the management of digital video and DOCSIS services. The Cisco RF Gateway 1 enables the converged next-generation cable access network by offering comprehensive video and DOCSIS functions in a single U-EQAM platform.

- True U-EQAM video (broadcast, SDV, SD/HD, MPEG-2, AVC) and high speed data (M-CMTS/DTI, DOCSIS 3.0) in 1 RU form factor
- Manual or DEPI Control Plane modes supported
- Table-based or session-based video functionality
- Optional on-board Encryption: DVB® SimulCrypt and PowerKEY® SKS
- Utilizes Direct Digital Synthesis (DDS) QAM technology which allows superior RF performance and stability
- 96 configurable QAM channels; each of which is fully agile 45–1000 MHz
- RF performance typically meets or exceeds CableLabs® DRFI specification CM-SP-DRFI
- Modular, hot-swappable, and Auto-configurable QAM cards
- Support for up to 2048 streams in 1 RU
- Fully redundant design with redundant Gigabit Ethernet ports and power supplies (AC/AC, AC/DC, or DC/DC)
- Front-to-back airflow to allow self-cooling and stacking
- Compliance with ITU-T J.83 standard, Annex A (DVB), Annex B (ATSC), or Annex C (Japan)
- Internet Group Management Protocol Version 3 (IGMPv3) support
- Low power consumption per QAM
- Four or eight QAM channels per RF port available - independent of channel bandwidth (6, 7, and 8 MHz)
- Fully SNMP compliant

## SPECIFICATIONS

GIGABIT ETHERNET INPUT INTERFACE	
Number of inputs	Number of inputs 2+2 (for redundancy) or 4 Independent
Connector	Optical/electrical Small Form Factor Pluggable (SFP)
Interface type	Gigabit Ethernet according to IEEE 802.3ab (Electrical) or IEEE 802.3z (Optical)
Input Data rate	Full line rate
Syntax	VBR and CBR MPEG SPTS and MPTS on UDP (RFC-768), RTP, L2TPv3, IGMPv3
Dejitter Buffering	500 ms (configurable from 5ms - 400ms)

RF OUTPUTS	
Number of outputs	Maximum 12 physical RF ports (each with 4 QAM channels)
Connector	F-type, 75 $\Omega$
Frequency	
Range	Channel edges between 45 and 1002 MHz (tunable)
Step size	1 kHz
Stability	$\pm 3$ ppm
Accuracy	$\pm 3$ ppm
Channel Bandwidth	6, 7, or 8 MHz depending on QAM transmission standard
Level	
8-Channel Mode	52 dBmV RMS Max per QAM Channel in 0.1 dB steps
4-Channel Mode	54 dBmV RMS Max per QAM Channel in 0.1 dB steps
3-Channel Mode	56 dBmV RMS Max per QAM Channel in 0.1 dB steps
2-Channel Mode	58 dBmV RMS Max per QAM Channel in 0.1 dB steps
1-Channel Mode	62 dBmV RMS Max per QAM Channel in 0.1 dB steps
Stability	$\pm 1$ dB
Accuracy	$\pm 1$ dB
Return loss	>14 dB 45-750 MHz >13 dB 750-870 MHz >12 dB 870-1000 MHz Per DOCSIS 3.0 DRFI specification CM-SP-DRFI
MANAGEMENT INTERFACE	
Interface type	Ethernet 10/100 BASE-T
Connector	RJ-45
Protocols	HTTP, SNMP, FTP, RPC
OTHER INTERFACES	
DTI	2 RJ-45 Primary and Redundant
Conditional Access	Ethernet 10/100 BASE-T
SIGNAL SPECIFICATIONS	
Channel encoding	Randomization, Reed-Solomon, Trellis Encoding, and Interleaving configurable to ITU Annex A, B, or C
MER (before equalizer)	$\geq 40$ dB (at RF)
MER (after equalizer)	$\geq 45$ dB (at RF)
QAM constellations	64 and 256 QAM
ENVIRONMENTAL SPECIFICATIONS	
Operating temperature	32 to 122°F (0 to 50°C)
Storage temperature	-30 to 158°F (-22 to 70°C)
Altitude	-200 to 10,000 feet AMSL
Operating humidity	5% to 95%, non-condensing
Power supply (nominal)	100 to 240 VAC or -48 VDC
Normal service voltage range	90 to 264 VAC or -38 to -58 VDC
Power consumption (fully loaded)	48 QAM Typical 345W 96QAM Typical x 360W
CHASSIS MECHANICAL SPECIFICATIONS	
Height	1.75 in. (44.45 mm) (1 RU)
Width	19 in. (482.6 mm)
Depth	21.0 in. (533.4 mm)
Weight	27.5 lbs (12.5 kg)

## ORDERING INFORMATION

PRODUCT NAME	PRODUCT DESCRIPTION
<b>Cisco RF Gateway 1 Chassis</b>	
RFGW-1	RFGW-1 with 2 Power Supply slots and 6 QAM Module slots. Includes Front Panel Display, IO Modules and Fans.
<b>Cisco RF Gateway 1 QAM Modules</b>	
RFGW-1-QAM-MOD	RFGW-1-D QAM MODULE (2x4QAM)
<b>Cisco RFGW-1 Power Supplies</b>	
RFGW-1-PS-AC	RFGW-1 AC power supply module
RFGW-1-PS-DC	RFGW-1 DC power supply module
<b>Cisco RF Gateway 1 Transceiver Modules</b>	
SFP-WDM-850-0500=	SFP WDM 850nm (up to 500m)
SFP-WDM-1310-5=	SFP WDM 1310nm (up to 5km)
SFP-CU-RJ45=	SFP Copper (RJ45)
<b>Cisco RF Gateway 1 Factory Installed Licenses (must configure with RFGW-1)</b>	
SWLIC-RFGW1-OCTAL	RFGW-1 Octal QAM License
SWLIC-RFGW1-DATA	RFGW-1 Data License
SWLIC-RFGW1-DVB	RFGW-1 DVB Session Based Scrambling License

SWLIC-RFGW1-PKEY	RFGW-1 PowerKey Scrambling License
<b>Cisco RF Gateway 1 eDELIVERY Upgrade Licenses</b>	
L-RFGW1-SWLIC=	PAK CONTAINER FOR RFGW-1 eDELIVERY License
L-RFGW1-OCTAL	RFGW-1 Octal QAM Upgrade License
L-RFGW1-DATA-LIC	RFGW-1 Data Upgrade License (2 required when combined with Octal License)
L-RFGW1-DVB	RFGW-1 DVB Session Based Scrambling Upgrade License (2 required when combined with Octal License)
L-RFGW1-PKEY	RFGW-1 PowerKey Scrambling Upgrade License (2 required when combined with Octal License)