


CISCO SIP 600

SPA INTERFACE PROCESSOR 600



PERFORMANCE ROUTING ENGINE COMPATIBILITY

Supported with ESR-PRE4 at 11.2 Gbps or ESR-PRE3 at reduced total Bandwidth of 5.6 Gbps. No SIP Support with PRE1 or PRE2.

MINIMUM SOFTWARE

Cisco IOS® Software Release 12.2(33)SB and later Releases

SLOT CONFIGURATION

Four single height SPAs, two double height SPAs, or combination

SUPPORTED SPAS

Ethernet
SPA-1X10GE-L-V2 Cisco 1-Port 10 GE SPA (XFP IEEE LAN PHY Optics)
SPA-5X1GE-V2 Cisco 5-Port GE SPA (SFP Optics)
SPA-2X1GE-V2 Cisco 2-Port GE SPA (SFP Optics or built in RJ-45 Ports)

INDICATORS

Single LED indicating whether the SIP Card has failed.
FAIL Indicator; Off (operational); On for more than five Seconds (faulty)
Note that SPAs include all Interface Status LEDs.

PHYSICAL

Occupies two line Card Slots and can be operated only in Cisco 10000 Series Router.
Weight: 6.3 lb (2.9 kg) (without SPAs)
Height: 2.4 in. (6.1 cm)
Width: 14.6 in. (37.1 cm)
Depth: 9.5 in. (24.1 cm)