

HOUSE AMPLIFIER PROFI-LINE BKE-PS

- BKE-PS amplifier: return way on board
- Precise and reliable adjustments by variable level attn. (PS) for level and slope control
- Low noise
- LED indicator for operation status
- Vodafone Kabel Deutschland GmbH certified



Types: BKE-PS

Type	BKE 22 PS-KDG	BKE 33 PS-KDG	BKE 36 PS-KDG	BKE 39 PS-KDG
Item No.	57002408 (PU:10)	57002409 (PU:10)	57002410 (PU:10)	57002411 (PU:10)
Description	57002595 (PU:1) ampl. with level attn.	57002596 (PU:1) ampl. with level attn.	57002597 (PU:1) ampl. with level attn.	57002598 (PU:1) ampl. with level attn.
Frequency range US / DS MHz	5-65 / 85-1006	5-65 / 85-1006	5-65 / 85-1006	5-65 / 85-1006
Gain US / DS dB	18 / 20	25 / 33	25 / 35	29 / 39
Adjustment level / slope DS dB	0 ... 20	0 ... 20	0 ... 20	0 ... 20
Interstage slope DS (Jumper)	0 / 7	0 / 7	0 / 7	0 / 7
Noise US/DS dB	5 / 6	5 / 6	5 / 6	5 / 6
Output level CENELEC42 flat dBμV	100	98	100	101
Return way (KDG 1TS140) dB	medium load	medium load	medium load	medium load
Level adjustment US dB	0 ... 20	0 ... 20	0 ... 20	0 ... 20
Slope return way dB	-	-	0/3/6/9	0/3/6/9
Test point	-	-	Input+Output	Input+Output
Power supply V~/W	230/7,5	230/8	230/8	185-265/6
Dimensions / Weight mm / kg	150 x 90 x 50 / 0.85	150 x 90 x 50 / 0.85	150 x 90 x 50 / 0.85	150 x 90 x 50 / 0.85
KDG class	B (1.1)	B (3.1)	B (3.2) + C (3.2)	C (4.2)

